

AUTO STEP DOWN TRANSFORMER 1PHASE : PO-02

คุณสมบัติของเครื่อง

หม้อแปลงลดแรงดันไฟฟ้า ใช้สำหรับลดแรงดันไฟฟ้า หรือจากแรงดันไฟสูงให้ต่ำลง เพื่อใช้กับอุปกรณ์ไฟฟ้า

ประเภทของงานที่ใช้

1. สำหรับเครื่องใช้ไฟฟ้าทั่วไปทุกชนิด ที่ใช้ไฟ 110 โวลท์เอซี 1 เฟส โดยแปลงจาก 220 โวลท์เอซี
2. สำหรับงานไฟฟ้าและอิเล็กทรอนิกส์ทุกชนิด ที่ต้องการขนาดแรงดันและกระแสเฉพาะงานโดยตรง (ระบุสเปคได้) ชนิด 1 เฟส



PO-02 Screen Type

รับประกันสินค้า 1ปี เฉพาะรุ่นที่ติดเบรกเกอร์เพิ่ม

SPECIFICATION			
Capacity	4500VA	5000VA	6000VA
Input Frequency	50-60 Hz		
Input Voltage	220Vac 1Phase		
Input Current	20 Aac.	22.7 Aac.	27.3 Aac.
Output Voltage	100 Vac (2 points), 110 Vac (2 points) 1Phase		
Output Current At 100 Vac	45 Aac.	50 Aac.	60 Aac.
Output Current At 110 Vac	40.9 Aac.	45.4 Aac.	54.5 Aac.
Cooling	Self Air		
Temperature	0 - 45 °c		
Efficiency	More than 97% At Full Load		
Insulation	Class B 130 °c		
Insulation Test	1000Vac. (rms.) For Transformer		
Insulation Resistance	More Than 10MΩ		
Input L, N, Ground	Cable Plug And Terminal In Box		
Output L, N, Ground	Plug Outlet Panasonic 100Vac, 110Vac And Terminal In Box		
Dimension (WxDxH)	PO-02 : 36.5 x 30 x 32 cm.		