

AUTOMATIC BATTERY CHARGER FOR FORKLIFT

INPUT 220V 1PHASE				
Model	Output Charger		Input Current	ขนาดแบตเตอรี่ 5-6 Hr.
	Volt	Current		
PT-12	24 V	80 A	16 A	380-490 Ah
PT-12	24 V	90 A	18 A	450-540 Ah
PT-12	24 V	100 A	20 A	480-620 Ah
PT-12	24 V	120 A	24 A	580-720 Ah
PT-12	24 V	140 A	27 A	700-840 Ah
PT-12	36 V	80 A	23 A	380-490 Ah
PT-12	36 V	90 A	25.3 A	450-540 Ah
PT-12	36 V	100 A	28.2 A	480-620 Ah
PT-12	36 V	120 A	34 A	580-720 Ah
PT-12	36 V	140 A	40 A	700-840 Ah

INPUT 380V 3PHASE				
Model	Output Charger		Input Current	ขนาดแบตเตอรี่ 5-6 Hr.
	Volt	Current		
PT-12	24 V	70 A	4 A	340-420 Ah
PT-12	24 V	80 A	4.5 A	380-490 Ah
PT-12	24 V	90 A	5 A	450-540 Ah
PT-12	24 V	100 A	6 A	480-620 Ah
PT-12	24 V	120 A	6.5 A	580-720 Ah
PT-12	24 V	130 A	8 A	650-780 Ah
PT-12	24 V	140 A	7.5 A	700-840 Ah
PT-12	24 V	150 A	10 A	750-900 Ah
PT-12	36 V	70 A	6.5 A	340-420 Ah
PT-12	36 V	80 A	7.3 A	380-490 Ah
PT-12	36 V	90 A	8.2 A	450-540 Ah
PT-12	36 V	100 A	9.2 A	480-620 Ah
PT-12	36 V	120 A	10.9 A	580-720 Ah
PT-12	36 V	140 A	12.8 A	700-840 Ah
PT-12	36 V	150 A	16 A	750-900 Ah
PT-12	48 V	70 A	7.3 A	340-420 Ah
PT-12	48 V	80 A	8.3 A	380-490 Ah
PT-12	48 V	90 A	9.2 A	450-540 Ah
PT-12	48 V	100 A	10.2 A	480-620 Ah
PT-12	48 V	120 A	12.3 A	580-720 Ah
PT-12	48 V	130 A	14.5 A	650-780 Ah
PT-12	72V	50 A	7.7 A	250-300 Ah
PT-12	72V	60 A	9.4 A	290-360 Ah
PT-12	72V	70 A	11 A	340-420 Ah
PT-12	72V	80 A	12.2 A	380-490 Ah
PT-12	80V	50 A	9.5 A	250-300 Ah
PT-12	80V	60 A	11 A	290-360 Ah
PT-12	80V	70 A	13 A	340-420 Ah
PT-12	80V	80 A	14.7 A	380-490 Ah

INPUT 220V 1PHASE				
Model	Output Charger		Input Current	ขนาดแบตเตอรี่ 5-6 Hr.
	Volt	Current		
PT-12	48 V	70 A	26.5 A	340-420 Ah
PT-12	48 V	80 A	29.3 A	380-490 Ah
PT-12	48 V	90 A	34 A	450-540 Ah
PT-12	48 V	100 A	37.5 A	480-620 Ah
PT-12	48 V	120 A	45 A	580-720 Ah
PT-12	48 V	140 A	53 A	700-840 Ah
PT-12	48 V	150 A	55 A	750-900 Ah
PT-12	72V	70 A	47 A	340-420 Ah
PT-12	72V	80 A	45.4 A	380-490 Ah

รับประกันสินค้า 1 ปี

SPECIFICATION					
Control System	Electronics SCR / Timer Control				
Timer System	Microcontroller Digital Timer Control				
Charger Control	Constant Voltage And Limit Current Charger				
Input Voltage	Ac 220v 1 Phase / Ac 380v 3 Phase				
Input Voltage Variable Range	±10%				
Input Frequency	50-60 Hz				
Output Charger For Battery	24Vdc	36Vdc	48Vdc	72Vdc	80Vdc
Output Voltage Max Constant Voltage	30V	45.5V	61V	90V	101V
Timer Operation At Output Voltage	29V	43.5V	58V	87V	96V
Output Voltage Accuracy	Less Than ±1.5%				
Output Current	Limit At Full Spec				
Timer Selector Switch	Normal 3 Hr / Equal 5 Hr				
Rectifier	Half Control Bridge SCR				
Temperature	45 °C				
Cooling System	By Air Convection				
Efficiency	More Than 75% At Full Load				
Rating	100% Continuous				
Over Load Time	150% For 5 Sec				
Indicator Lamp	Charge Ind. / Gassing 80% Ind. / Complete Ind. / O/P Fuse Ind.				
Function Of Select Display	Show Digital Timer, Volt-Amp Meter				
Protection	Input Ac Output Over Charger Output Dc Input Ac Control Safety Charger Cut Off Safety Battery				
	Breaker Limit Current Circuit Soft Start 5-10 Sec, Power Fuse By Fuse 10 Hr. Battery Opposite Pole Disconnect				
Transformer	Isolation Class H. (180 ° C)				
Dimension (W x D x H) Cm.	58 x 55 x 65.5 Cm.				