

AUTOMATIC BATTERY CHARGER FOR FORKLIFT

INPUT 220V 1PHASE				
Model	Output Charger		Input	ขนาดแบตเตอรี่ 5-6 Hr.
	Volt	Current	Current	
PT-11	24 V	30 A	6 A	140-170 Ah
PT-11	24 V	40 A	8 A	180-250 Ah
PT-11	24 V	50 A	10 A	250-300 Ah
PT-11	24 V	60 A	12 A	290-360 Ah
PT-11	24 V	70 A	14 A	340-420 Ah
PT-11	36 V	30 A	8.5 A	140-170 Ah
PT-11	36 V	40 A	12 A	180-250 Ah
PT-11	36 V	50 A	14.4 A	250-300 Ah
PT-11	36 V	60 A	17 A	290-360 Ah
PT-11	36 V	70 A	20 A	340-420 Ah
PT-11	48 V	30 A	11.2 A	140-170 Ah
PT-11	48 V	35 A	13.5 A	175-210 Ah
PT-11	48 V	40 A	14.8 A	180-250 Ah
PT-11	48 V	50 A	18.3 A	250-300 Ah
PT-11	48 V	60 A	22.5 A	290-360 Ah
PT-11	72V	30 A	16 A	140-170 Ah
PT-11	72V	40 A	27 A	180-250 Ah
PT-11	72V	50 A	34 A	250-300 Ah
PT-11	72V	60 A	40 A	290-360 Ah



SPECIFICATION					
Control System	Electronics SCR / Timer Control				
Timer System	Microcontroller Digital Timer Control				
Charger Control	Constant Voltage And Limit Current Charger				
Input Voltage	Ac 220v 1 Phase Ac 380v 3 Phase				
Input Voltage Variable Range	±10%				
Input Frequency	50-60 Hz				
Output Charger For Battery	24Vdc	36Vdc	48Vdc	72Vdc	80Vdc
Output Voltage Max Constant Voltage	30V	45.5V	61V	90V	101V
Timer Operation At Output Voltage	29V	43.5V	58V	87V	96V
Output Voltage Accuracy	Less Than ±1.5%				
Output Current	Limit At Full Spec				
Timer Selector Switch	Normal 3 Hr / Equal 5 Hr				
Rectifier	Half Control Bridge SCR				
Temperature	45 °C				
Cooling System	By Air Convection				
Efficiency	More Than 75% At Full Load				
Rating	100% Continuous				
Over Load Time	150% For 5 Sec				
Indicator Lamp	Charge Ind. / Gassing 80% Ind. / Complete Ind. / O/P Fuse Ind.				
Function Of Select Display	Show Digital Timer, Volt-Amp Meter				
Protection	Input Ac	Breaker			
	Output Over Charger	Limit Current Circuit			
	Output Dc	Soft Start 5-10 Sec, Power Fuse			
	Input Ac Control	By Fuse			
	Safety Charger Cut Off	10 Hr.			
	Safety Battery	Battery Opposite Pole Disconnect			
Transformer	Isolation Class H. (180 °C)				
Dimension (W x D x H) Cm.	47.5 x 50.5 x 55 Cm.				

รับประกันสินค้า 1ปี

INPUT 380V 3PHASE				
Model	Output Charger		Input	ขนาดแบตเตอรี่ 5-6 Hr.
	Volt	Current	Current	
PT-11	24 V	30 A	1.8 A	140-170 Ah
PT-11	24 V	40 A	2.3 A	180-250 Ah
PT-11	24 V	50 A	2.8 A	250-300 Ah
PT-11	24 V	60 A	3.5 A	290-360 Ah
PT-11	36 V	30 A	2.7 A	140-170 Ah
PT-11	36 V	40 A	3.6 A	180-250 Ah
PT-11	36 V	50 A	4.6 A	250-300 Ah
PT-11	36 V	60 A	5.5 A	290-360 Ah
PT-11	48 V	30 A	3.3 A	140-170 Ah
PT-11	48 V	35 A	4 A	175-210 Ah
PT-11	48 V	40 A	4.4 A	180-250 Ah
PT-11	48 V	50 A	5.3 A	250-300 Ah
PT-11	48 V	60 A	6.3 A	290-360 Ah
PT-11	72 V	30 A	5 A	140-170 Ah
PT-11	72 V	40 A	6.3 A	180-250 Ah
PT-11	80 V	30 A	6 A	140-170 Ah
PT-11	80 V	40 A	7.8 A	180-250 Ah