

DC POWER SUPPLY AND AUTOMATIC BATTERY CHARGER **PT-02A**



PT-02A

SPECIFICATION

Control System	Switching DC Power Supply/ Timer
Charger Control	Constant Voltage And Limit Current
Cooling System	Blower
Input Voltage	220Vac. -20% +15% (176-253Vac)
Input Current	N/A
Input Frequency	50 Hz.
Output Charger	For Battery 24Vdc. and 48Vdc.
Charger Voltage	Float : 27.5Vdc
	Equal : 29.2Vdc (Automatic Switch To Float Charge By Timer 0-30Hr)
Output Voltage Regulation	±1.5%
Efficiency	More Than 90% At Full Load (Output Max V, A)
Temperature	0 - 40 °c
Transformer	Isolation
Rectifier	Full Bridge
Protection	Input Breaker
	Output Limit Current And Fuse
Filter	Reactor, Capacitor
Indicator	Output Ind., Equal Ind., Float Ind., Output Fuse Ind.
	Output Analog Amp Meter, Output Analog Volt Meter Solid State Timer
Dimension (W x D x H)	24.5 x 43.5 x 35 Cm.
Weight	15.5 Kg.

คุณสมบัติของเครื่องชาร์จแบตเตอรี่ PT-02A

เป็นทั้งเครื่องชาร์จแบตเตอรี่แบบอัตโนมัติและเป็นแหล่งจ่ายไฟดีซี. ระบบ SWITCHING POWER SUPPLY / TIMER CONTROL มีความเที่ยงตรงและประสิทธิภาพสูง มีรีเลย์และการสูญเสียที่ต่ำมาก

ประโยชน์ของเครื่องชาร์จแบตเตอรี่ PT-02A

- ใช้ชาร์จแบตเตอรี่ได้ทั้งแบบน้ำและแบบแห้ง
- FOR STARTING BATTERY
- SEALED LEAD ACID BATTERY
- DEEP CYCLE BATTERY (แบตเตอรี่น้ำ)

รุ่น	ชาร์จกับแบตเตอรี่	กระแสไฟชาร์จ
PT-02A	24V	34A
PT-02A	24V	60A
PT-02A	24V	100A
PT-02A	48V	34A