

AUTOMATIC CUT OFF BATTERY CHARGER : CH-1202 x 4CH

เครื่องชาร์จอัตโนมัติ ชนิดเต็มแล้วตัด เบ็นชาร์จฟื้นฟูแบตเตอรี่

คุณสมบัติของเครื่องชาร์จแบตเตอรี่ CH-1202

เป็นเครื่องกระตุ้นชาร์จแบตเตอรี่ที่เสื่อมสภาพ เนื่องจากปล่อยไว้เป็นเวลานานโดยไม่ได้ทำการชาร์จ ซึ่งอาจทำให้ชาร์จไฟไม่เข้าแบตเตอรี่ จึงต้องกระตุ้นชาร์จด้วยแรงดันที่สูงขึ้นและมีกระแสต่ำๆ ชาร์จและดีสชาร์จเป็นระยะๆ สามารถช่วยฟื้นฟูกำลังไฟแบตเตอรี่ได้ใกล้เคียงกับแบตเตอรี่ลูกใหม่ หลังจากแบตเตอรี่ถูกกระตุ้นจนรับไฟแล้ว ระบบจะทำการชาร์จอัตโนมัติจนแบตเตอรี่เต็ม หากแบตเตอรี่ลูกไหนที่เสื่อมสภาพมาก ๆ ถ้าถูกกระตุ้นแล้วไม่สามารถฟื้นฟูได้ เครื่องจะส่งสัญญาณ FAIL รุ่น CH-1202 จะชาร์จได้พร้อมกันสูงสุด 4 ตัว

ประโยชน์ของเครื่องชาร์จแบตเตอรี่ CH-1202

- ใช้ชาร์จแบตเตอรี่ทั้งแบบห้าและแบบแห้ง
 - ใช้ชาร์จกระตุ้นแบตเตอรี่ที่เสื่อมประสิทธิภาพ
- (แบตเตอรี่ที่ไม่ถูกใช้เป็นเวลานาน ๆ, แบตเตอรี่ที่ชาร์จไฟไม่เข้า)
- ใช้ชาร์จแบตเตอรี่มอเตอร์ไซค์, แบตเตอรี่รถยนต์ขนาดเล็ก

CH-1202



SPECIFICATION	
Control System	MCU Control
Charger System	Constant Voltage And Limit Current
Input Voltage	AC 220V ±10% 50Hz 1Phase
Input Current	1.2 Aac
Input Protection	Fuse
Output Charger	For Battery 12 Vdc
Output Current	1.5, 2A x 4 Ch.
Output Protection	Output Limit And Fuse
Transformer	Isolation
Temperature	0 - 45 °c
Cooling System	Self Air Cooling
Efficiency	More Than 80% At Full Load
Insulation Resistance	More Than 5MΩ For Transformer
LED Indicator	Start, Status Charge, Pass, Fail, Output Fuse
Dimension (WxDxH)	74 x 35.5 x 27 mm.