

AUTO STEP DOWN TRANSFORMER 1PHASE : PO-01

คุณสมบัติของเครื่อง

หม้อแปลงลดแรงดันไฟฟ้า ใช้สำหรับลดแรงดันไฟฟ้า หรือจากแรงดันไฟสูงให้ต่ำลง เพื่อใช้กับอุปกรณ์ไฟฟ้า

ประเภทของงานที่ใช้

1. สำหรับเครื่องใช้ไฟฟ้าทั่วไปทุกชนิด ที่ใช้ไฟ 110 โวลท์เอซี 1 เฟส โดยแปลงจาก 220 โวลท์เอซี
2. สำหรับงานไฟฟ้าและอิเล็กทรอนิกส์ทุกชนิด ที่ต้องการขนาดแรงดันและกระแสเฉพาะงานโดยตรง (ระบุสเปคได้) ชนิด 1 เฟส



รับประกันสินค้า 1 ปี เฉพาะรุ่นที่ติดเบรกเกอร์เพิ่ม

PO-01 Screen Type

SPECIFICATION				
Capacity	2500VA	3000VA	3500VA	4000VA
Input Frequency	50-60 Hz			
Input Voltage	220Vac 1Phase			
Input Current	11.4 Aac.	13.6 Aac.	15.9 Aac.	18.2 Aac.
Output Voltage	100 Vac (2 points), 110 Vac (2 points) 1Phase			
Output Current At 100 Vac	25 Aac.	30 Aac.	35 Aac.	40 Aac.
Output Current At 110 Vac	22.7 Aac.	27.3 Aac.	31.8 Aac.	36.4 Aac.
Cooling	Self Air			
Temperature	0 - 45 °c			
Efficiency	More than 97% At Full Load			
Insulation	Class B 130 °c			
Insulation Test	1000Vac. (rms.) For Transformer			
Insulation Resistance	More Than 10MΩ			
Input L, N, Ground	Cable Plug And Terminal In Box			
Output L, N, Ground	Plug Outlet Panasonic 100Vac, 110Vac And Terminal In Box			
Dimension (WxDxH)	PO-01 : 25 x 22 x 24 cm.			