

MANUAL BATTERY CHARGER MODEL : TK

คุณสมบัติ

ใช้ซิลิคอนไอโอด 4 ตัว (Bridge Rectifier) สำหรับแปลงไฟเอ.ซี. เป็น ดี.ซี

- จะกินไฟน้อยกว่าระบบที่ใช้ไดโอดตัวเดียว แต่ให้กำลังไฟชาร์จได้แรงกว่า ทำให้จ่ายค่าไฟน้อยกว่าขณะที่ใช้งานเหมือนกัน
- เกิดความร้อนขณะใช้งานน้อยกว่าทั้งตัวแบตเตอรี่และตัวเครื่องชาร์จ
- รูปคลื่นไฟออกเรียบกว่า ทำให้อายุการใช้งานของแบตเตอรี่ยาวนานมากขึ้น
- มีประสิทธิภาพสูง และเกิดการสูญเสียน้อยกว่า อีกทั้งน้ำหนักของเครื่องจะเบาลง

MODEL : TK



รับประกันสินค้า 1 ปี

SPECIFICATION	
Input voltage	220Vac. 1phase (200-250Vac.)
Input current	1.6 Aac.
Input frequency	50-60 Hz.
Output charger	Select 6, 12, 18, 24 Vdc
Output current	12 Amps rms
For Battery	Lead-Acid 3-150Ah.
Rectifier	Bridge diode
Coil Transformer	Copper
Efficiency	More than 80% at full load
Cooling system	Self air cooling
Temperature	0 - 45 °C
Transformer	Isolation Type
Control panel	Power switch, adjust volt, adjust amp
Over Load Protection	Input by fuse Output by fuse
Indicator	Input lamp switch, Amp meter
Auxiliary	Complete with supply cord and plug, Output cable and clips.
Dimension (W x D x H)	28 x 20 x 21.5 Cm.
Weight	7.6 Kg