

Pure Sine Wave Inverter : 24V, 48V



2500W



3000W



5000W 24V



4000W



5000W 48V

PRODUCT FEATURES :

- Pure sine wave output
- Frequency switch : choose 50Hz or 60Hz
- High Surge : high surge current capability starts difficult loads such as TVs,camps,motors and other inductive loads.
- Soft start : smooth start-up of the appliances.
- Cooling fan works automatically
- Low harmonic distortion : below 3%.
- Two LED show the working and failure state.

APPLICATION FOR :

- Solar electric energy generation
- Communication equipment
- Industrial intellectual control system
- Emergency power supply system

Model	PH524-2500	PH524-3000	PH524-4000	PH524-5000	PH548-5000
Rated Power	2500W	3000W	4000W	5000W	5000W
Surge Power (few seconds)	5000W	6000W	8000W	10000W	10000W
Input Voltage	24VDC				48VDC
Output Voltage	220VAC				
Frequency	50/60Hz				
Output Waveform	Pure Sine Wave				
Soft Start	YES				
Low Voltage Alarm	19.6VDC				40.1VDC
Low Voltage Shut Down	19.2VDC				38.5VDC
Over Voltage Alarm	31.6VDC				61.1VDC
Over Voltage Shut Down	31.6VDC				61.1VDC
Dimension (L×W×H)	415×165×82mm	270×151×85mm	325×165×92mm	390×167×90mm	415×165×82mm
N.W./Unit	7.2kg	7.8kg	9.2kg	9.2kg	9.2kg